

## Cisco WRP400: Wireless-G Broadband Router with 2 Phone Ports

### Mobile Broadband USB Modem Compatibility List

#### File Details

Table 1 lists the current firmware version and filenames for the Cisco® WRP400 Wireless-G Broadband Router.

**Table 1.** Current Firmware for the Cisco WRP400

Firmware version	2.00.05 (FCC and ETSI)
Firmware release date	February 2009

#### USB Modem Compatibility

Table 2 lists the USB modems that are compatible with the Cisco WRP400.

**Table 2.** USB Modems Compatible with the Cisco WRP400

Make	Model	Technology	Service Provider*
Novatel	U720	EVDO Rev 0/A	Sprint/Verizon
Novatel	U727	EVDO Rev 0/A	Sprint/Verizon
Huawei	E172	HSDPA	AT&T/Vodafone
Huawei	E220	HSDPA	AT&T/Vodafone
Huawei	E270	HSDPA	AT&T/Vodafone
Huawei	E272	HSDPA	AT&T/Vodafone
Sierra Wireless	AC595U	EVDO Rev 0/A	Sprint/Verizon
Sierra Wireless	597U Compass	EVDO Rev 0/A	Sprint
Sierra Wireless	875U	HSDPA	AT&T
Sierra Wireless	880U	HSDPA	AT&T
Sierra Wireless	881U	HSDPA	AT&T

\* May also be used with other service provider 3G networks.

#### USB Modem Initialization and Connection Status via the Power LED

- During installation, the Power LED of the Cisco WRP400 will indicate the progress of the initialization of the USB modem.
- After the USB modem is successfully installed, the behavior of the Power LED will indicate the status of the mobile network connection (Table 3).

**Table 3.** Status Indicated by WRP400 Power LED

LED Behavior	USB Modem Status
<b>Steady green</b>	<ul style="list-style-type: none"> <li>• Before the USB modem is connected, indicates that the WRP400 has power.</li> <li>• After the USB modem is connected, indicates that the initialization was successful. If the WRP400 is configured to use the mobile network connection as a failover, the Power LED will remain steady green.</li> </ul>
<b>Flashing green/orange</b>	<ul style="list-style-type: none"> <li>• Indicates that a device is connected to the USB port and initialization is in progress.</li> <li>• If continuous, indicates that the WRP400 failed to initialize the USB modem.</li> </ul>
<b>Flashing orange</b>	<ul style="list-style-type: none"> <li>• Indicates that the WRP400 is attempting to connect to the Internet through the mobile network connection.</li> <li>• If continuous, indicates that the WRP400 failed to connect to the Internet through the mobile broadband network connection and is trying again.</li> </ul>
<b>Steady orange</b>	Indicates that the WRP400 is connected to the Internet through the mobile broadband network connection.

**Note:**

- The WRP400 will automatically attempt to connect to the mobile network via the USB modem when inserted.
- If an Internet connection is already established via the Ethernet WAN port, the USB modem will be used as a failover connection.
- Only one interface can be used to establish a link at a time. By default, the WRP400 uses the Ethernet WAN connection when available.

**WRP400 Documentation and Support**

- Cisco WRP400 User Guide
- Cisco WRP400 Quick Start Guide
- Cisco WRP400 Mobile Broadband USB Modem FAQ
- Cisco WRP400 Mobile Broadband USB Modem Compatibility List

Available at: <http://www.cisco.com/en/US/products/ps10028/index.html>.

**Help and Support at Cisco Community Central**

<https://www.myciscocommunity.com/community/smallbizsupport>.



**Americas Headquarters**  
Cisco Systems, Inc.  
San Jose, CA

**Asia Pacific Headquarters**  
Cisco Systems (USA) Pte. Ltd.  
Singapore

**Europe Headquarters**  
Cisco Systems International BV  
Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

CCDE, CCENT, Cisco Eos, Cisco HealthPresence, the Cisco logo, Cisco Lumin, Cisco Nexus, Cisco StadiumVision, Cisco TelePresence, Cisco WebEx, DCE, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn and Cisco Store are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0812R)